

4.5.4.5 Contact Arrangement

The number of contacts shall be as shown in Figure 2(b) and contact arrangements shall be indicated by the codes specified hereafter.

CODE	SHELL SIZE	NUMBER OF CONTACTS GAUGE 20	NUMBER OF CONTACTS GAUGE 22	NUMBER OF COAXIAL AND/OR POWER CONTACTS	CAVITIES (NOTE 1)
9	E	9	0	0	
5W1	E	4	0	1	
15	A	15	0	0	
15	E	0	15	0	
3W3	A	0	0	3	
3WK3	A	0	0	3 (1) (2)	
7W2	A	5	0	2	
11W1	A	10	0	1	
25	B	25	0	0	
26	A	0	26	0	
5W5	B	0	0	5	
9W4	B	5	0	4	
13W3	B	10	0	3	
17W2	B	15	0	2	
21W1	B	20	0	1	
37	C	37	0	0	
8W8	C	0	0	8	
13W6	C	7	0	6	
17W5	C	12	0	5	
21WA4	C	17	0	4 (2) (3)	
21W4	C	17	0	4 (2) (3)	
25W3	C	22	0	3	
27W2	C	25	0	2	
44	B	0	44	0	
50	D	50	0	0	
24W7	D	17	0	7	
36W4	D	32	0	4	
43W2	D	41	0	2	
47W1	D	46	0	1	
62	C	0	62	0	
78	D	0	78	0	
104	F	0	104	0	

- NOTES**
1. (see attached)
 2. 1. 2 male plus 1 female or 2 female plus 1 male (see Para. 4.5.4.6).
 3. 2. See Figure 2 for physical differences.

Para 4.5.4.5

Note 1

Cavities,

~~4.5.4.10 Contact Information~~

For connectors with contact arrangements that include coaxial or power contacts, the coaxial or power contacts shall be ordered separately in accordance with ESCC Detail Specification Nos. 3401/004 and 3401/040 respectively.

~~EQ = Connector ordered without coaxial or power contacts. This information shall only be marked on the packaging and not marked on the connector.~~

Coaxial and power contacts must be from the same Manufacturer as the connector in which they are mounted and this shall be verified prior to assembly.